

Joule heating generated by spin current through Josephson junctions

S. Takahashi,* T. Yamashita, T. Koyama, and S. Maekawa
Institute for Materials Research, Tohoku University, Sendai 980-8577, Japan

H. Imamura
Graduate School of Information Sciences, Tohoku University, Sendai 980-8579, Japan

We theoretically study the spin-polarized current flowing through a Josephson junction (JJ) in a spin injection device. When the spin-polarized current is injected from a ferromagnet (FM) in a superconductor (SC), the charge current is carried by the superconducting condensate (Cooper pairs), while the spin-up and spin-down currents flow in the equal magnitude but in the opposite direction in SC, because of no quasiparticle charge current in SC. This indicates that not only the Josephson current but also the spin current flow across JJ at zero bias voltage, thereby generating Joule heating by the spin current. The result provides a new method for detecting the spin current by measuring Joule heating at JJ.

Spin transport through a nonmagnetic metal has attracted much interest in magnetic nanostructures. In the tunnel junctions consisting of a ferromagnet (FM) and a normal metal (N) or superconductor (SC), the tunnel current driven from FM is spin-polarized [1] and creates a nonequilibrium spin population in N or SC [2,3]. Recently, there has been a number of experiment on suppression of superconductivity by injection of spin-polarized electrons using tunnel junctions of a high- T_c SC and a ferromagnetic manganite [4,5,6].

A double tunnel junction with a thin layer of SC sandwiched between two FM electrodes is a unique system to investigate a novel magnetoresistive effect caused by nonequilibrium spin population in SC. When the thickness of SC layer is much smaller than the spin diffusion length, the spin population depends strongly on the relative orientation of magnetizations in FMs. In the antiparallel alignment of magnetizations, the spin population is accumulated in SC and reduces the superconducting gap Δ with increase of tunneling currents, while in the parallel alignment there is no such effect because of the absence of spin accumulation in SC [7]. In contrast, the spin current flows in SC in the parallel alignment, but not in the antiparallel alignment [8]. Although several methods for detecting the spin accumulation has been presented, there is little for the spin current. In this paper, we propose a new method for detecting the spin current flowing in SC using a Josephson junction (JJ). We show that the spin current flows through JJ even at zero bias voltage ($V_J = 0$), thereby generating Joule heating at JJ. Since there is no quasiparticle charge current across JJ at $V_J = 0$, the Joule heating generated at $V_J = 0$ is a direct signature of the spin current flowing in SC.

We consider a spin injection device made of FM and SC separated by thin insulating layers as shown in Fig. 1. The central part of the junction forms the Josephson junction, which is sandwiched between two FMs. The left and right SC (FM) are made of the same SC (FM). The magnetization of the left FM points up and that of the right FM is either up or down. The applied bias

current I_{inj} flows through the junctions of resistances R_J and R_T with the voltage drops V_J and V_T , respectively.

We calculate the tunneling current using a phenomenological tunneling Hamiltonian that describes the transfer of electrons from one electrode to the other. If SC is in the superconducting state, it is convenient to rewrite the electron operators $a_{\mathbf{k}\sigma}$ in SC in terms of quasiparticle operators $\gamma_{\mathbf{k}\sigma}$ appropriate to the superconducting states, using the Bogoliubov transformation [9]

$$a_{\mathbf{k}\uparrow} = u_{\mathbf{k}}\gamma_{\mathbf{k}\uparrow} + v_{\mathbf{k}}^*\hat{S}\gamma_{-\mathbf{k}\downarrow}^\dagger, \quad a_{-\mathbf{k}\downarrow}^\dagger = -v_{\mathbf{k}}\hat{S}^\dagger\gamma_{\mathbf{k}\uparrow} + u_{\mathbf{k}}^*\gamma_{-\mathbf{k}\downarrow}^\dagger,$$

where $|u_{\mathbf{k}}|^2 = \frac{1}{2}(1 + \xi_{\mathbf{k}}/E_{\mathbf{k}})$, $|v_{\mathbf{k}}|^2 = \frac{1}{2}(1 - \xi_{\mathbf{k}}/E_{\mathbf{k}})$, $\hat{S}$ is an operator which annihilates a Cooper pair, while $\hat{S}^\dagger$ creates one, and $E_{\mathbf{k}} = [\xi_{\mathbf{k}}^2 + \Delta^2]^{1/2}$ is the quasiparticle dispersion of SC, $\xi_{\mathbf{k}}$ being the one-electron energy relative to the chemical potential of the condensate and Δ being the isotropic superconducting gap.

From the Fermi's golden rule result, the spin-dependent tunnel currents $I_{i\sigma}$ across the i th junction are expressed as [7]

$$I_1^\uparrow(V_T) = (G_{1\uparrow}/e) [\mathcal{N} - \mathcal{S}_1], \quad (1a)$$

$$I_1^\downarrow(V_T) = (G_{1\downarrow}/e) [\mathcal{N} + \mathcal{S}_1], \quad (1b)$$

$$I_2^\uparrow(V_T) = (G_{2\uparrow}/e) [\mathcal{N} + \mathcal{S}_2], \quad (1c)$$

$$I_2^\downarrow(V_T) = (G_{2\downarrow}/e) [\mathcal{N} - \mathcal{S}_2]. \quad (1d)$$

Here, $G_{i\sigma}$ ($i = 1, 2$) is the tunnel conductance for electrons with spin σ when SC is in the normal state. The quantity $\mathcal{N}$ is given by the usual expression

$$\mathcal{N}(V_T) = \int_{-\infty}^{\infty} \mathcal{D}_S(E) [f_0(E - eV_T) - f_0(E)] dE, \quad (2)$$

where $\mathcal{D}_S(E) = \text{Re} [|E|/\sqrt{E^2 - \Delta^2}]$ is the normalized BCS density of states and $f_0(E)$ the Fermi function. The quantity $\mathcal{S}_i$ is the quasiparticle spin density accumulated in SC




FIG. 1. Spin injection device consisting of a Josephson junction (SC-I-SC) which is sandwiched between two ferromagnets (FM). The arrows indicate the injection current, pair current, and quasiparticle current in SCs, and the Josephson current (solid arrow) and spin current (dotted arrow) across JJ, in the case of parallel alignment of magnetizations in FMs whose spin polarization is 100 %.

$$\mathcal{S}_i = \frac{1}{2} \int_{-\infty}^{\infty} \mathcal{D}_S(E) [f_{i\uparrow}(E) - f_{i\downarrow}(E)] dE, \quad (3)$$

where $f_{i\sigma}(E_{\mathbf{k}}) = \langle \gamma_{\mathbf{k}\sigma}^\dagger \gamma_{\mathbf{k}\sigma} \rangle_i$ is the distribution function of quasiparticles with energy $E_{\mathbf{k}}$ and spin σ in the i th SC. In Eq. (1), we neglected the charge imbalance (Q^*) since it has no relevance to the spin-dependent effect [8].

In the limit of vanishing spin-flip scattering in SC, the spin-up and spin-down currents are treated as independent channels. The conservation of the total charge current $I_{\text{inj}} = I_i^\uparrow + I_i^\downarrow$ and the spin current $I_{\text{spin}} = I_i^\uparrow - I_i^\downarrow$ across the left and right junctions yields the relations

$$I_{\text{inj}} = \frac{1}{eR_T} [\mathcal{N} - \frac{1}{2} (P_1 \mathcal{S}_1 - P_2 \mathcal{S}_2)], \quad (4)$$

$$I_{\text{spin}} = \frac{1}{2eR_T} [(P_1 + P_2) \mathcal{N} - (\mathcal{S}_1 - \mathcal{S}_2)], \quad (5)$$

where $1/R_T = G_{i\uparrow} + G_{i\downarrow}$ and $P_i = (G_{i\uparrow} - G_{i\downarrow}) / (G_{i\uparrow} + G_{i\downarrow})$. P_i represents the degree of spin-polarization of FM. In the parallel alignment, $P_1 = P_2 = P$ and $\mathcal{S}_1 = -\mathcal{S}_2 = \mathcal{S}$, so that

$$I_{\text{inj}} = \frac{1}{eR_T} (\mathcal{N} - P\mathcal{S}), \quad I_{\text{spin}} = \frac{1}{eR_T} (P\mathcal{N} - \mathcal{S}). \quad (6)$$

In the antiparallel alignment, $P_1 = -P_2 = P$ and $\mathcal{S}_1 = \mathcal{S}_2 = P\mathcal{N}$, so that

$$I_{\text{inj}} = (eR_T)^{-1} (1 - P^2) \mathcal{N}, \quad I_{\text{spin}} = 0. \quad (7)$$

The tunnel current across JJ has the form

$$I_{\text{inj}} = I_{\text{qp}}(V_J) + I_{J1}(V_J) \sin \varphi + I_{J2}(V_J) \cos \varphi, \quad (8)$$

for a bias voltage V_J and a phase difference φ of the gap parameters on the two side of JJ. The first term describes the quasiparticle tunneling, and second and third

terms describe the phase coherent (Cooper pair) tunneling. The usual Josephson effect is associated with the $\sin \varphi$ term. Using the golden rule formula, we have the spin-dependent tunnel current of quasiparticles

$$I_{\text{qp}}^\sigma(V_J) = \frac{1}{2eR_J} \int_{-\infty}^{\infty} \mathcal{D}_S(E) \mathcal{D}_S(E + eV_J) \times [f_{1\sigma}(E) - f_{2\sigma}(E + eV_J)] dE, \quad (9)$$

with which the quasiparticle charge current I_{qp} and the spin current I_{spin} across JJ are written as

$$I_{\text{qp}} = I_{\text{qp}}^\uparrow(V_J) + I_{\text{qp}}^\downarrow(V_J), \quad (10)$$

$$I_{\text{spin}} = I_{\text{qp}}^\uparrow(V_J) - I_{\text{qp}}^\downarrow(V_J). \quad (11)$$

The phase coherent tunneling terms are obtained as

$$I_{J1} = \frac{\Delta^2}{eR_J} \int_{-\infty}^{\infty} dE \frac{\mathcal{D}_S(E) \mathcal{D}_S(E + eV_J)}{|E(E + eV_J)|} \times \sum_{j=1}^2 [1 - f_{j\uparrow}(|E|) - f_{j\downarrow}(|E|)], \quad (12)$$

$$I_{J2} = \frac{\Delta^2}{eR_J} \int_{-\infty}^{\infty} dE \frac{\mathcal{D}_S(E) \mathcal{D}_S(E + eV_J)}{E(E + eV_J)} \times \sum_{\sigma} [f_{2\sigma}(E + eV_J) - f_{1\sigma}(E)]. \quad (13)$$

When the thickness of SC is much smaller than the spin diffusion length, the distribution of quasiparticles is spatially uniform in SC. Then, the distribution function $f_{i\sigma}$ is described by f_0 , but the chemical potentials of the spin-up and spin-down quasiparticles are shifted oppositely by $\delta\mu_i$ from the equilibrium one to create the spin density;

$$f_{i\uparrow}(E) = f_0(E - \delta\mu_i), \quad f_{i\downarrow}(E) = f_0(E + \delta\mu_i). \quad (14)$$

The gap parameter Δ in SCs is determined by $f_{i\sigma}$ through the BCS gap equation

$$\ln \left[\frac{\Delta}{\Delta_0} \right] + \int_{\Delta}^{\infty} \frac{f_{i\uparrow}(E) + f_{i\downarrow}(E)}{\sqrt{E^2 - \Delta^2}} dE = 0, \quad (15)$$

where Δ_0 is the gap at $T = 0$ in the equilibrium state ($\delta\mu_i = 0$).

In the following we calculate the tunnel current at zero bias voltage ($V_J = 0$). In this case, a DC Josephson current flows across JJ unless the bias current exceeds the Josephson critical current $J_c = I_J(0)$. From Eq. (11), we notice that I_{spin} in the parallel alignment becomes finite even at $V_J = 0$ if $\delta\mu_1$ and $\delta\mu_2$ take nonzero values of different sign ($\delta\mu = \delta\mu_1 = -\delta\mu_2$), while I_{spin} in the antiparallel alignment is zero because of $\delta\mu = \delta\mu_1 = \delta\mu_2$. The currents I_{J2} and I_{qp} vanish at $V_J = 0$ irrespective of the value of $\delta\mu_i$. These facts indicate that the Josephson current as well as the spin current flow across JJ at $V_J = 0$ in the parallel alignment, while only the Josephson current flows in the antiparallel alignment.




FIG. 2. Joule heating W as a function of temperature at zero bias ($V_J = 0$) in the parallel alignment of magnetizations in FMs. Inset shows half the spin splitting of the chemical potential of quasiparticles in SC.

We consider, for simplicity, the case where FM is a half-metal with 100 % spin polarization ($P = 1$), in which the spin current is equal to the injection current, $I_{\text{inj}} = I_{\text{spin}}$, because only the spin-up electrons are injected into SC. Figure 1 shows how the current $I_{\text{inj}} = I^\uparrow$ is injected from the left FM in SC and how the spin and charge currents flow in SCs and pass through JJ in the parallel alignment. In SC, the charge current is carried by the superconducting condensate (Cooper pairs) alone; there is no charge current carried by quasiparticles ($I_{\text{qp}}^\uparrow + I_{\text{qp}}^\downarrow = 0$), so that the spin-up and spin-down currents flow in the opposite direction with the value of $I_{\text{qp}}^\uparrow = -I_{\text{qp}}^\downarrow = I^\uparrow/2$. In other words, the half of $I^\uparrow$ is injected to be the spin-up current $I_{\text{qp}}^\uparrow$ in SC, and the other half of $I^\uparrow$ injected in SC is combined with the backflow spin-down current $I_{\text{qp}}^\downarrow$ to form the pair current I_{pair} . It is remarkable that the spin current is able to pass through JJ at zero bias ($V_J = 0$). This is because the voltage drop across JJ is positive for the spin-up current, while it is negative for the spin-down current, resulting in no net voltage drop across JJ. Therefore, the spin current as well as the Josephson current flow through the JJ at $V_J = 0$, the magnitude of which is equal to I_{inj} in the half-metallic case.

The most striking prediction of the present theory is that the spin current across JJ is accompanied by Joule heating W at zero bias voltage ($V_J = 0$). The Joule heating W generated at $V_J = 0$ is given by $W = I_{\text{spin}}(\delta\mu_1 - \delta\mu_2)/e$. In the parallel alignment ($\delta\mu = \delta\mu_1 = -\delta\mu_2$),

$$W = 2I_{\text{spin}}\delta\mu/e, \quad (16)$$

while in the antiparallel alignment $W = 0$ because of $I_{\text{spin}} = 0$ and $\delta\mu = \delta\mu_2 = \delta\mu_1$, indicating that the Joule heating generated by spin current has strong spin-dependence.

Figure 2 shows the Joule heating W normalized to $W_0 = \Delta_0^2/e^2R_J$ as functions of temperatures for the injection current $I_{\text{inj}}/J_{c0} = 0.1$ and 0.2 in the parallel alignment [10], where $J_{c0} = \pi\Delta_0/(2eR_J)$ is the Josephson critical current. As the temperature is lowered, W increases monotonically. This is due to the increase of the spin-splitting of $\delta\mu$ (see the inset) in the current bias mode. A slight decrease of the critical temperature and a depression of W near T_c in the curve of $I_{\text{inj}}/J_{c0} = 0.2$ is caused by the pair breaking effect by spin accumulation in SC. The power of Joule heating W generated by spin current is estimated by evaluating the value of W_0 , since W is comparable to W_0 . If one uses the values of an area resistance $R_J\mathcal{A} = 100 \Omega\mu\text{m}^2$ and $\Delta_0 = 0.3 \text{ meV}$ (Al), we have $W_0/\mathcal{A} = 90 \text{ mW/cm}^2$ per area of JJ. Therefore, W is fairly large for observing the Joule heating experimentally.

In conclusion, we propose a new method for detecting the spin current by measuring the Joule heating generated at JJ. This is attributed to the fact that the spin-up and spin-down currents flow in the opposite direction in SC. For measuring the Joule heating, it may be important for the tunnel junctions to satisfy the condition $R_J \gg R_T$, in order to make the Joule heating W dominant compared with the injection power ($I_{\text{inj}}^2 R_T$).

We are grateful to M. Johnson and J. S. Moodera for valuable discussions. This work is supported by a Grant-in-Aid for Scientific Research Priority Area for Ministry of Education, Science and Culture of Japan, NEDO Japan, and by the supercomputing facilities in IMR, Tohoku University.

-
- [1] R. Meservey and P. M. Tedrow, Phys. Rep. **238**, 173 (1994).
 - [2] M. Johnson and R. H. Silsbee, Phys. Rev. Lett. **55**, 1790 (1985); Phys. Rev. B **37**, 5326 (1988).
 - [3] M. Johnson, Appl. Phys. Lett. **65**, 1460 (1994).
 - [4] V. A. Vas'ko *et al.*, Phys. Rev. Lett. **78**, 1134 (1997).
 - [5] Z. W. Dong *et al.*, Appl. Phys. Lett. **71**, 1718 (1997).
 - [6] N.-C. Yeh *et al.*, Phys. Rev. B **60**, 10522 (1999).
 - [7] S. Takahashi, H. Imamura, and S. Maekawa, Phys. Rev. Lett. **82**, 3911 (1999); J. Appl. Phys. **85**, 5227 (2000).
 - [8] S. Takahashi *et al.* Physica C, (2000).
 - [9] B. D. Josephson, Phys. Lett. **1**, 251 (1962); M. Tinkham, *Introduction to Superconductivity* (McGraw-Hill, New York, 1996).
 - [10] To avoid a spurious logarithmic divergence arising from convolving the BCS density of states with an isotropic gap in Eq. (11), we introduce a small broadening in the BCS density of states using Dynes's formula $\mathcal{D}_S(E) = \text{Re}[(E - i\gamma)/\sqrt{(E - i\gamma)^2 - \Delta^2}]$ with broadening parameter γ much less than Δ .